



Model: PWPC1-120V-1200W

## Pre-wired, 120V AC, Adjustable Electric Power Controller



### FEATURES & BENEFITS

- 120V AC Model Controls Up to 1200 Watts
- 8' Rubberized Power Input Cord
- 0-100% Adjustable Power Output Control
- Red Mushroom Rapid Shutdown Switch
- Red "Power On" Pilot Light
- User Resettable 10A Circuit Breaker

### APPLICATIONS

- Electric Brew Pot Control, Food Processing
- Electric Heater Linear Power Control

### DESCRIPTION

Model PWPC1-120V-1200W – Adjustable Electric Power Controller provides reliable user adjustable 120V AC power control. The unit features a Benchtop or wall mountable console design, built-in SCR, adjustable 0-100% control dial, user resettable circuit breaker, power-on indicator, heavy duty integral power and output cords.

### General Specifications

Enclosure Rating:	NEMA 1 (For indoor use only)
Enclosure Material:	Painted Cast Aluminum
Input Voltage:	90-125V AC, 50/60 Hz
Power Control:	Adjustable, 0-100%
Max Output Load:	1200 Watts (Resistive)
Circuit Breaker:	10A, User Resettable
Power Input Cord:	8' Rubberized with 3-Prong Male Plug
Power Output Cord:	2' Rubberized with 3-Prong Female Plug
Mounting:	Wall or Benchtop



© 2017 :: Imagine Instruments LLC, 4500 Williams Drive, Ste 212-318, Georgetown, TX 78633, p. (855)574-6243  
e-mail: [info@imagineinstruments.com](mailto:info@imagineinstruments.com), [www.imagineinstruments.com](http://www.imagineinstruments.com)

Note: Continued product improvements make specifications subject to change without notice.  
Check [www.imagineinstruments.com](http://www.imagineinstruments.com) for the latest product information and updates

Released: 8 January, 2017 :: Rev: A